

# Photodiode as current source

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Photo Diode as current source ..... 2

### Photo Diode as current source



Fig. 2: Inverting Op-Amp: Photo Diode BPW 34 S



Fig. 3: Inverting Op-Amp: Diagramms of BPW 34 S



Fig. 4: Inverting Op-Amp: Photo Diode as current source

$$U_{DD} \approx 10\text{V}, U_{SS} \approx -10\text{V}$$

We assume a good illuminated room of 300 lx, illuminated by a white LED. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm. For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths. For an easier calculation, we take a mean value of 500 nm which is close to the peak value of the blue LED (in reality a greenish light) and 300 lx for the illumination. In the diagram in figure 3 we see that the sensitivity of the photo diode at 500 nm is only 30%. The maximum current (100%) at 300 lx is 30  $\mu\text{A}$ . Now we can calculate the current we expect from the diode at 300 lx:

$$I_1 = 30\ \mu\text{A} * 0.3$$

$$I_1 \approx 10\ \mu\text{A}$$

30% of 30  $\mu\text{A}$  is roughly 10  $\mu\text{A}$ .

Complete the arrows in the schematic of the circuit. Calculate  $R_2$  so that  $U_{OUT} = 5\text{V}$  at 300 lx. Take a resistor from the E6 series that is as close as possible to the calculated value.

$$I_D = ?$$

$$I_2 = ?$$

$U_{OUT}$

$U_2$

$R_2$

What value would you expect for  $U_D$  and why?

$U_D$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

What value would you expect for  $U_D$  when it is not connected to the Op-Amp or any other electronic component (open-circuit voltage) at 300 lx?

$U_D$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

$\{\rm \dots\}$

From:  
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:  
[https://wiki.mexle.org/lab05\\_en/inverting\\_op-amp\\_photo\\_diode\\_as\\_current\\_source?rev=1776676034](https://wiki.mexle.org/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776676034)

Last update: **2026/04/20 11:07**

