Photodiode as current source

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Photodiode as current source 2

Photodiode as current source



Fig. 2: Inverting Op-Amp: Photodiode BPW 34 S



Fig. 3: Inverting Op-Amp: Diagramms of BPW 34 S



Fig. 4: Inverting Op-Amp: Photo Diode as current source

$U_{\rm DD}{\rm~=10~V},~U_{\rm SS}{\rm~=-10~V}$

We assume a good illuminated room of 300 lx, illuminated by a white LED. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm.
For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths.
For an easier calculation, we take a mean value of 500 nm which is close to the peak value of the blue LED (in reality a greenish light) and 300 lx for the illumination.
The graph in figure 3 shows that the photodiode sensitivity at 500 nm is only 30%. The maximim current (100%) at 300 lx is 30 ${\rm\mu}$A.
We can now estimate the current we would expect from the photodiode at 300 lx:

$I_{\rm 1} = 30 {\rm~\mu A} * 0.3 = 9 {\rm~\mu A}$
$I_{\rm 1} \approx 10 {\rm~\mu A}$

30% of 30 ${\rm\mu A}$ is roughly 10 ${\rm\mu A}$.
We will asume a 10 ${\rm\mu A}$ at 300 lx for our calculations.

Complete the arrows in the scematic of the circuit.
Calculate ${\rm R_2}$ so that $U_{\rm OUT}$ = 5 V at 300 lx. Take a resistor from the E6 series that is as close as possible to the calculated value.
Also fill in the values for $I_{\rm 1}$, $I_{\rm 2}$, $U_{\rm OUT}$ and $U_{\rm 2}$.

$I_{\rm 1}{\rm~=}$

$I_{\rm 2}{\rm~=}$

$U_{\rm OUT}{\rm~=}$

$U_{\rm 2}{\rm~=}$

$R_{\rm 2}{\rm~=}$

What value would you expect for $U_{\rm D}$ and why?

$U_{\rm D}{\rm~=}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

What value would you expect for $U_{\rm D}$ at 300 lx when it is not connected to the Op-Amp or any other electronic component (open-circuit voltage) and why?

$U_{\rm D}{\rm~=}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

${\rm .....}$

Illumination	\(U_{\rm OUT}\) [...	\(I_{\rm 1}\) [µA...	\(I_{\rm 2}\) [µA...	\(U_{\rm D}\) [mV...	\(U_{\rm D}\) [mV...
dark...					
300 lx...		...			

Tab. 1: Photodiode measured values

From:
https://wiki.mexle.org/ - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.org/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776688621

Last update: **2026/04/20 14:37**