

# Photodiode as current source

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Photodiode as current source ..... 2

### Photodiode as current source



Fig. 2: Inverting Op-Amp: Photodiode BPW 34 S



Fig. 3: Inverting Op-Amp: Diagramms of BPW 34 S



Fig. 4: Inverting Op-Amp: Photo Diode as current source

$$U_{DD} = 10\text{ V}, U_{SS} = -10\text{ V}$$

We assume a good illuminated room of 300 lx, illuminated by a white LED. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm. For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths. For an easier calculation, we take a mean value of 500 nm which is close to the peak value of the blue LED (in reality a greenish light) and 300 lx for the illumination. The graph in figure 3 shows that the photodiode sensitivity at 500 nm is only 30%. The maximum current (100%) at 300 lx is 30  $\mu\text{A}$ . We can now estimate the current we would expect from the photodiode at 300 lx:

$$I_1 = 30\ \mu\text{A} * 0.3 = 9\ \mu\text{A}$$

$$I_1 \approx 10\ \mu\text{A}$$

30% of 30  $\mu\text{A}$  is roughly 10  $\mu\text{A}$ .

**We will assume a current of 10  $\mu\text{A}$  at 300 lx for our calculations.**

Complete the arrows in the schematic of the circuit in figure 4.

Calculate  $R_2$  so that  $U_{OUT} = 5\text{ V}$  at 300 lx. Take a resistor from the E6 series that is as close as possible to the calculated value.

Also enter the values for  $I_1$ ,  $I_2$ ,  $U_2$  and  $U_{OUT}$ .

$$I_1 = \text{ } \mu\text{A}$$

$I_{\text{2}} \approx$

$U_{\text{2}} \approx$

$U_{\text{OUT}} \approx$

$R_{\text{2}} \approx$

What value would you expect for  $U_{\text{D}}$  and why?

$U_{\text{D}} \approx$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

$\{ \dots \}$

What value would you expect for  $U_{\text{D}}$  at 300 lx when it is not connected to the Op-Amp or any other electronic component (open-circuit voltage) and why?

$U_{\text{D}} \approx$

$\text{mV}$  .....

$\text{mV}$  .....

$\text{mV}$  .....

$\text{mV}$  .....


$\text{mV}$  .....

$\text{mV}$  .....

Measure or calculate the values given in the table below.

Illumination	$(U_{\text{OUT}})$ [mV]	$(I_{\text{1}})$ [ $\mu\text{A}$ ]	$(I_{\text{2}})$ [ $\mu\text{A}$ ]	$(U_{\text{D}})$ [mV]	$(U_{\text{D}})$ [mV]
dark...					X
300 lx...		...			

Tab. 1: Photodiode measured and calculated values



From:  
<https://wiki.mexle.org/> - **MEXLE Wiki**

Permanent link:  
[https://wiki.mexle.org/lab05\\_en/inverting\\_op-amp\\_photo\\_diode\\_as\\_current\\_source?rev=1776696423](https://wiki.mexle.org/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776696423)

Last update: **2026/04/20 16:47**

