

Resistance measurement

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Resistance measurement

Background Information

Experimental Tasks

Direct resistance measurement

Indirect resistance measurement

Test Questions - Resistors

.....

.....

.....

.....

.....

.....

2

2

2

2

3

3

Resistance measurement

Background Information

Procedure for resistance measurement: * Set the measuring device to resistance measurement * Connect the resistance to be measured to the corresponding sockets on the measuring device (the measuring device sockets labeled COM and Ω) * Read the measured value in text * How * How * How There are different types of resistance measurement: * **direct** resistance measurement * **indirect** resistance measurement The resistances can also be determined by measuring the current/voltage. **Ohm's law: In an electrical circuit, the current increases with increasing voltage and decreases with increasing resistance.**

$$I = \frac{U}{R}$$

Experimental Tasks

Direct resistance measurement

Determine the nominal and measured values of the resistance for R_1 (brown, green, orange), R_2 (yellow, violet, red), R_3 (red, violet, red) and the incandescent lamp R_L . Also measure the approximate resistance R_K of your body from your right to

your left hand.

	R_1	R_2	R_3	R_L	R_K
nominal value					
measured value					

Tab. 1: Direct resistance measurement

How do you explain the deviation between $R_{L,nominal}$ and $R_{L,meas}$?

What consequences can R_K have?

Now determine the series and parallel connections of resistors R_1 , R_2 and R_3 .

Specify the formulas used:

$R_{\text{serial}} =$

$R_{\text{parallel}} (= R_a || R_b) =$

	R_1+R_2	R_1+R_3	R_2+R_3	$R_1 R_2$	$R_1 R_3$	$R_2 R_3$
calculated						
measured						

Tab. 2: Series and parallel connections

Indirect resistance measurement

Build the measuring circuit shown in [figure 1](#) for each of the three resistors and set the voltage on the power supply to $\sim 12\text{ V}$.




Fig. 1: Indirect resistance measurement Measure U_{n} [V] and I_{n} [mA]. Calculate R_{n} [k Ω]

I_1	U_1	R_1	I_2	U_2	R_2	I_3	U_3	R_3

from these values.

Tab. 3: Indirect resistance measurement

Test Questions - Resistors

From:
<https://wiki.mexle.org/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.org/mexlefirst_public/resistance-measurement?rev=1786451789

Last update: 2026/08/11 14:36